

Radio Frequency Repeater

Our Radio Frequency Repeater provides up to 300 metres in signal distance between a radio frequency systems' transmitter and its portable receivers, working on internationally compatible frequencies.

Contacta RF systems support 40 selectable channel groups to allow for a wide array of applications such as multilanguage interpretation and tour guidance.

Designed for free-standing installations, the Repeater's compact and elegant housing means it can be placed anywhere. The device is powered using its provided portable USB power supply.

contacta | II.

RF-RP

Applications

Ideal for situations where listeners require clear sound, tour guidance or interpretation:

- Museums
- Historical Sites
- Meeting Rooms
- Conferences
- Places of Worship

Components

- Radio Frequency Transmitter
- USB Power Supply

Talk to us now: +44 (0) 1732 223900 (UK & ROW) +1 616 392 3400 (US & Canada) www.contacta.co.uk



Physical Data

	Height – 37mm (1.45")
Dimensions	Width – 230mm (9.05") Depth – 124mm (4.88")
Weight	555g (1.22lbs)
Finish	Black



Technical Data

USB Power Supply	5V/DC - 1A	
Operation Frequency	2.4 GHz (ISM)	
Modulation	Modulation FSK, with hopping	
Range	300m outdoors 100m in buildings	
Channel	40 simultaneous groups	
Frequency Response	50Hz – 7kHz	
Transmitting Power	10mW	
Sensitivity	-95dBm	
Speech Coding	16bit/8KHz	
Delay	<35ms	
Frequency Width	2MHz	
Data Transmission Rate	2Mbps	
Connections Sockets	1x 6.3mm jack plug LINE IN 1x 3-PIN XLR AUDIO IN/OUT 1x 3.5mm jack plug headset IN 1x 4-PIN XLR headset IN	
Display	2x LCD display (group, channel, volume, mode, signal strength)	